

AEP APPROVED MULTI-GANG METER SOCKET/BREAKER COMBINATION CENTERS

Note: AEP does not support the use of K-base meter bases. All meter sockets shall be Underwriters Laboratories Listed and labeled as such. 100 and 200 amp 4 terminal meter sockets shall have provisions for a 5th terminal and bypass horns for utilities use for manual bypass using jumper cables. 200 amp 5 and 7 terminal and all 320 amp meter sockets shall have a good quality jaw release manual operated bypass which is 100% rated. Minimum 125A block rating required for 100 amp meter socket. Minimum rated 22KAIC standard required. All sockets shall be ringless.

Barrels lock provision 7/8 inch required on each cover.

Eaton Cutler Hammer

USE	# POS	SERIES	NAME	RATING
IN/OUTDOOR	2 - 6	1MP	Meter Packs	125-200A/POS
IN/OUTDOOR	3 - 5	1MM	MODULAR MTR'G	125A/POS
IN/OUTDOOR	3 - 4	1MM	MODULAR MTR'G	200A/POS
IN/OUTDOOR	3 - 5	3MM	MODULAR MTR'G	125A/POS
IN/OUTDOOR	3 - 4	3MM	MODULAR MTR'G	200A/POS
IN/OUTDOOR	1-4	35MM/37MM	COMM'L-STACK	200A/320A POS

GE - GENERAL ELECTRIC

USE	# POS	SERIES	NAME	RATING
IN/OUTDOOR	2 - 5	TMP	METER MOD	125-200A/POS
IN/OUTDOOR	2 - 6	TMM	MINI MOD	125-200A/POS

SIEMENS/Talon

USE	# POS	SERIES	NAME	RATING
OUTDOOR	2 - 6	WMM/WMLxxxxxRJB	MODULAR METERING	125A/200A/POS
OUTDOOR	2 - 6	WPxxxxRJB WPLxxxxRJ WTGxxxxRJB WTGLxxxxRJ	UNI-PAK	125A/200A/POS

AEP APPROVED MULTI-GANG METER SOCKET/BREAKER COMBINATION
CENTERS

SQUARE D

USE	# POS	SERIES	NAME	RATING
IN/OUTDOOR	1 – 4	EZML-7	EZ METER PAK	200A/POS
IN/OUTDOOR	1	C125RB	CSED	125A/POS
IN/OUTDOOR	3-6	EZMH	EZ METER PAK	125A/POS
IN/OUTDOOR	3-5	EZMH	EZ METER PAK	200A/POS
IN/OUTDOOR	2 – 6	MP	METER PAK	125-200A/POS

CHALLENGER

USE	# POS	SERIES	NAME	RATING
INDOOR	2-6	SMT/1SMT	ALL N'ONE	125A/POS
OUTDOOR	2-6	WMT/1WMT	ALL N'ONE	125A/POS
INDOOR	2-6	BMT/1BMT	ALL N'ONE	150-200A/POS
OUTDOOR	2-6	RBMT/1RBMT	ALL N'ONE	150-200A/POS

Milbank

USE	# POS	SERIES	NAME	RATING
OUTDOOR	2-6	U5902-BLG U5906-BLG	Meter Pack	125A/POS
OUTDOOR	2-6	U5882-BLG U5886-BLG	Meter Pack	200A/POS